

HD / Skylink® Garage Door Receiver

With Security+ 2.0 Compatibility

Your Harley Davidson / Skylink® garage door receiver has been modified to work with your Security+ 2.0 garage door opener. Typical brands that support this technology are Chamberlain, Liftmaster and Craftsman AssureLink, but there may be others. If your particular opener supports MyQ technology and/or Security+ 2.0, then this modification will work for you.

Your modified receiver has been thoroughly tested, including pairing with an actual Harley Davidson garage door opener transmitter (P/N 91561-01B) which uses the bike's high beam switch to control the opener. Because of this pairing & testing, you may need to renew the pairing with your own transmitter. If this is a new receiver, pairing *will* be required. In addition, the new Security+ 2.0 module inside your receiver will need to be sync'd with your garage door opener. Please read the instructions thoroughly, and if you have any questions, please contact me via email at the address on the last page.

Connect the control wire:

The control wire that plugs into the back of the receiver must be connected to the two wires that run between the wall control and the garage door opener. The receiver can be placed at any location where the control wire can reach either the wall control or the garage door opener. Connect the **red** wire from the receiver to the **red** wire for the wall control (or the wire that connects to the red terminal if the colors are different). Connect the **black** wire from the receiver to the **white** wire for the wall control (or the wire that connects to the white terminal if the colors are different). Plug the receiver into an electrical outlet.

Pair the receiver to the transmitter

You may need two people to perform this step (an alternative would be to do the pairing before plugging in the control wire to the back of the receiver, and power the receiver from an extension cord that will reach the bike).

1. Turn on the bike's ignition (but don't start it).
2. With the receiver plugged in to power, press and hold the button on the front of the receiver (the red LED will flash).
3. While holding the button, cycle the high beam switch from low to high and back (about 1 second for the complete cycle). The red LED on the receiver will go out. If it doesn't, cycle the high beam switch again.
4. Once the red LED is out, the transmitter and receiver have been paired. Release the button on the receiver and test the pairing by cycling the high beam switch again. You should hear the receiver click.

Sync the Security+ 2.0 module to the opener

After pairing, make sure the control cable is plugged into the back of the receiver and the receiver has power (red light is on). Turn the bike's ignition on (don't start it) and cycle the high beam switch. You should hear the receiver click and the red LED will momentarily go off and come back on. You may have to perform this step up to three times before the receiver will sync. Once it syncs, the garage door will open/close whenever you cycle the high beam switch.

Troubleshooting

In testing, the receiver pairing remains intact even if the receiver is unplugged for extended periods of time. However, if you find that the garage door opener is not responding, please try the following steps:

1. Make sure the receiver has power (red LED is on).
2. Make sure the wall control operates the door (if so, verify your control wire connections from the receiver).
3. Does the receiver click (and the red LED momentarily go out) when you cycle the high beam switch? If not, perform the pairing steps outlined above.
4. If the receiver is responding to the transmitter, but the opener is not working, repeat the syncing procedure above.
5. When pairing the receiver, don't hold it too close to the bike's transmitter. If you are having difficulty pairing the receiver to the bike, try moving it a little further away.

If the steps above do not resolve the issue, please contact me via email at Support@CreativeAccessSolutions.com for further assistance.

Warranty

The interface module installed inside your receiver is covered by a 1-year warranty. If it fails during the first 365 days after you receive it, ship it back and it will be replaced at no charge, including return shipping. The foregoing also applies to your receiver *only if* you purchased a new receiver as part of a bundle. If we modified your existing receiver, then only the components added by the modification are covered.

You must first request an RMA by sending an email to: Support@CreativeAccessSolutions. Include your name and order number (if purchased direct) or eBay user ID and approximate date of purchase.